Amplifiers

Return path filters

WFS 130 222262
WFS 165 222263
WFS 166 20910010

- Suitable for the VOS 135/G, VOS 135/P and VOS 136/G house connection amplifiers
- Consists of two filter boards, complete for input and output
- Please order separately (not supplied with VOS 13x/x)
- Packing unit/weight (pc./kg): 1 (10)/0.03

Type Order no.	Symbol		Frequency range (MHz)				
			Return path 5-30	Return path 30-65	Forward path 47-80	Forward path 80-85	Forward path 85-862
WFS 130 222262		Through loss (dB)	**0.5**		**0.5**		
WFS 165 222263		Through loss (dB)	**0.5**			**0.5**	
WFS 166 20910010		Through loss (dB)	**0.5**				**0.5**

De-emphasis equalisers

ERZ 100 272790
ERZ 101 20910011

- To equalise the pre-emphasis at the start of the distribution level in 862 MHz networks
- Suitable for VOS 135/G and VOS 136/G house connection amplifiers
- Please order separately (not supplied with VOS 13x/x)

Type		**ERZ 100**	**ERZ 101**
Order no.		272790	20910011
Frequency range		47-862	47-862
Equaliser value, continuously adjustable (862 MHz)	dB	0-15 (470-862 MHz)	0-10 (47-862 MHz)
Basic loss (47 MHz)	dB	0-2.5 (47-470 MHz)	0.5 (47 MHz)
Packing unit/weight	pc./kg	1 (10)/0.01	1 (10)/0.01